

JE-11SSP-8M

# Data Sheet

**jensen transformers**  
INCORPORATED

LINE INPUT TRANSFORMER

## REVISED HOOK-UP FOR IMPROVED TRANSIENT PERFORMANCE

USE HOOK-UP CHART BELOW IN PLACE OF HOOK-UP PRINTED  
ON TRANSFORMER -

		<u>JUMPER</u>	<u>SIGNAL HI</u>	<u>SIGNAL LO</u>
PRI	600 $\Omega$	1-4	2	3
	150 $\Omega$	1-3, 2-4	2	3
SEC	600 $\Omega$	6-7	8	5*
	150 $\Omega$	5-7, 6-8	8	5*

\* PIN 5 OF SECONDARY IS PREFERRED GROUND. -

IF POLARITY INVERSION IS DESIRED, REVERSE PRIMARY LEADS.

SHIELD = PIN 9

CASE = PIN 10

TRANSFORMERS USING THIS HOOK UP EXHIBIT FAR  
LESS OVERTSHOOT & RINGING THAN WITH PREVIOUS HOOK-UP  
PRINTED ON TRANSFORMER CASE.

REVISED 1-29-85

SAH